

# **Safety Precautions**

- Important Notes on exporting this product or equipment containing this product;
   If the end-user or application of this product is related to military affairs or weapons, its export may be controlled by "Foreign Exchange and Foreign Trade Control Law" of Japan where export license will be required before product can be exported from Japan.
- This product is designed and manufactured for use in General Purpose Industrial Equipment and it is not intended to be used in equipment or system that may cause personal injury or death.
- All servicing such as installation, wiring, operation, maintenance and etc., should be performed by qualified personnel only.
- Tighten mounting screws with an adequate torque by taking into consideration strength of the screws and the characteristics of material to which the product will be mounted. Over tightening can damage the screw and/or material; under tightening can result in loosening.
- · Install safety equipment to prevent serious accidents or loss that is expected in case of failure of this product.
- Consult us before using this product under such special conditions and environments as nuclear energy control, aerospace, transportation, medical equipment, various safety equipments or equipments which require a lesser air contamination.
- We have been making the best effort to ensure the highest quality of our products, however, some applications with exceptionally large external noise disturbance and static electricity, or failure in input power, wiring and components may result in unexpected action. It is highly recommended that you make a fail-safe design and secure the safety in the operative range.
- If the motor shaft is not electrically grounded, it may cause an electrolytic corrosion to the bearing, depending on the condition of the machine and its mounting environment, and may result in the bearing noise. Checking and verification by customer is required.
- Failure of this product depending on its content may generate smoke of about one cigarette. Take this into consideration when the application of the machine is clean room related.
- Please be careful when using the product in an environment with high concentrations of sulfur or sulfuric gases, as sulfuration can lead to disconnection from the chip resistor or a poor contact connection.
- Do not input a supply voltage which significantly exceeds the rated range to the power supply of this product. Failure to heed this caution may lead to damage of the internal parts, causing smoke and/or fire and other troubles.
- The user is responsible for matching between machine and components in terms of configuration, dimensions, life expectancy, characteristics, when installing the machine or changing specification of the machine. The user is also responsible for complying with applicable laws and regulations.
- · Manufacturer's warranty will be invalid if the product has been used outside its stated specifications.
- Component parts are subject to minor change to improve performance.
- Read and observe the instruction manual to ensure correct use of the product.

Repair

Consult to the dealer from whom you have purchased this product for details of repair work.

 $When the \ product \ is \ incorporated \ to \ the \ machine \ you \ have \ purchased, \ consult \ to \ the \ machine \ manufacturer \ or \ its \ dealer.$ 

URL

Electronic data of this product (Instruction Manual, CAD data) can be downloaded from the following web site; industrial.panasonic.com/ac/e/

Contact to



Panasonic Industry Co., Ltd., Industrial Device Business Division

1-1 Morofuku 7-chome, Daito, Osaka 574-0044, Japan



Search



2023.9



# **AC Servo Motor & Driver**

MINAS A6 Family 400 V Series

# IN Better Solution



2023.9

# **Motor line-up**

MINAS A6 400 V Series

- •Battery-less absolute encoder motor : Absolute system can be configured without the battery.
- European connector motor : Angled receptacle.

	200 w	400 w	750 w	850 w	1000 w	1.0 kW	1.3 kw	1.5 kW	1.8 kW	2.0 kW	2.4 kW	2.9 kW	3.0 kW	4.0 kW	4.4 kw	5.0 kw
Low inertia  MSMF  400 V		le description Flange s dimensi [Unit: mn	on			100 sq.		100 sq.		100 sq.			120 sq.	130 sq.		130 sq.
Rated speed (Max. speed)						3000 r/min(5500 r/min)	)	 	J	<b>3000</b> r/m	in(5500 r/min)			3(	000 r/min(5000 r/n	
Middle inertia  MDMF  400 V						130 sq.		130 sq.		130 sq.			130 sq.	176 sq.		—176 sq.
Rated speed (Max. speed)						2000 r/min(3500 r/min)		 	J		2000 r/min(3500 r/r	_   nin)		l		2000 r/min(3000 r/min
Middle inertia/ Low speed high torque  MGMF  400 V				130 sq.			130 sq.		130 sq.		176 sq.	176 sq.			176 sq.	
Rated speed (Max. speed)				1500 r/min(3500 r/min)			1500 r/min(3500 r/min)	 	1500 r/min(3500 r/min)		1500 r/min(3000 r/min	1500 r/min(3500 r/min)			1500 r/min(3000 r/min)	
High inertia <b>MHMF</b> 400 V	60 sq.	60 sq.	80 sq.		80 sq.	130 sq.		130 sq.		176 sq.			176 sq.	176 sq.		—176 sq.
Rated speed (Max. speed)	<b>3000</b> r/mir	n(6500 r/min)		3000 r/min(6000 r/min	)	2000 r/min(3500 r/min)		 			2 <b>000</b> r/min(3500 r/r	.   nin)		l		2000 r/min(3000 r/min

<sup>•</sup> Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

# **INDEX** A6 Family 400 V series Line - up...... 1 Model Designation.....4 Table of Part Numbers and Options ........ 5 Motor Motor Specifications ......7 Dimensions of Motor......17 Motor Specification Description......23 Driver Specifications......25 A6SF series ..... Dimensions of Driver ......29

Please refer to the A6BF series specifications homepage.

# Multi Servo Drive System

Launched in European market only



# MINAS A6 Multi: New 400 V Servo Drive System

Multi-axis drive system for compact and safe automation solutions targeting Europe as the main target.


- 1 Saving Space (2-axis control, book style design)
- **2** Reduced wiring (DC link, EtherCAT)
- 3 Advanced safety integrated
- 4 Reduce installation and maintenance hours (DC link, EoE, FoE<sup>\*1</sup>, FSoE<sup>\*1</sup>)
- 5 European connector motor
- 6 Battery less / safety encoder

\*1 Under development planning

# **Driver line-up**


MINAS A6

 Lineup of three types of network driver EtherCAT, Realtime Express, Modbus.



Higl	n speed communication F	or Realtime Express N	letwork servo dri
	RTEX Realtime Express	Rotary motor  Multifunction type  A6NF series	Linear motor DD motor  Multifunction type  A6NM ser  Special order product
Control mode	Position/Speed/ Torque control	•	
Contro	Full-close control		
Interface	External scale		
	STO (Safety Torques Off)		

# **Servo drivers with EtherCAT open network**



<sup>\*1</sup> When using internal speed command with Modbus, external servo ON is required. •Please check the instruction manual for necessary wiring. Special order product For more information, please visit our website or request to our distributors separately. •Please refer to the A6BF series specifications homepage.

Refer to P.5 to P.6 for motor and driver combinations.

# Servo Motor

M S M F 1 0 4 L 1 C 9
1 3 4 5 6 7

Special specifications
M: Special order product

\*1 Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

#### ① Type

Symbol	Туре					
MSM	Low inertia	(1.0 kW to 5.0 kW)				
MDM	Middle inertia	(1.0 kW to 5.0 kW)				
MGM	Middle inertia	(0.85 kW to 4.4 kW)				
MHM	High inertia	(0.2 kW to 5.0 kW)				

#### 2 Series

Symbol	Series name
F	A6 Family

# **3 Motor rated output**

Symbol	200 W 400 W 750 W		Symbol	Rated output
02			18	1.8 kW
04			20	2.0 kW
08			24	2.4 kW
09	0.85 kW (130 sq)	Н	29	2.9 kW
09	1000 W (80 sq)		30	3.0 kW
10	1.0 kW		40	4.0 kW
13	1.3 kW		44	4.4 kW
15	1.5 kW		50	5.0 kW

#### 4 Voltage specifications

	Symbol	Specifications
H	4	400 V

#### 5 Rotary encoder specifications

Symbol	Format	Pulse counts	Resolution	Wires
L	Absolute	23-bit	8388608	7
Α	Batteryless absolute	23-bit	8388608	5

#### <Note>

When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

#### 6 Design order

Symbol	Specifications
1	Standard

Motor specifications: 100 mm sq. to 176 mm sq. MSMF 1.0 kW to 5.0 kW

MDMF 1.0 kW to 5.0 kW MGMF 850 W to 4.4 kW MHMF 1.0 kW to 5.0 kW

Symbol		Sh	aft	Holding	g brake	Oil seal	
		Round	Key-way	without	with	without	With protective lip
С	9	•		•		•	
С	Α	•		•			•
D	9	•			•	•	
D	Α	•			•		•
G	9		•	•		•	
G	Α		•	•			•
Н	9		•		•	•	
Н	Α		•		•		•

#### ⑦ Motor specifications: 80 mm sq. or less MHMF 200 W to 1000 W

	Symbol		Shaft		Holding	g brake	Oil seal	
S			mbol Round Key-way		without	without with		With protective lip
-	Α	9	•		•		•	
E	В	9	•			•	•	
(	С	9	•		•			•
[	D	9	•			•		•
	S	9		•	•		•	
-	Т	9		•		•	•	
ι	U	9		•	•			•
١	V	9		•		•		•

#### Servo Driver



## 1) Frame symbol

Symbol	Frame
MDD	D-Frame
MED	E-Frame
MFD	F-Frame

#### 2 Series

Symbol	Series name
L	A6 Family

#### **3 Safety Function**

-		-
Frame	Symbol	Specifications
D-Frame	Т	with the safety function
E-Frame		
F-Frame	(4) Max.	current rating

# Indicates the difference in the applicable motor (or output rating).

# (5) Supply voltage specifications

@ Gabb	ny vonago opocinican
Symbol	Specifications
4	3-phase 400 V

## **(6)** I/f specifications 7 Classification of type

Symbol (specification)	Symbol	Specification
S	F	Multi fanction type (Pulse, analog, full-closed)
(Analog/Pulse)	М	Multifunction for linear/DD motor
N	F	Multifunction for rotary motor
(RTEX)	М	Multifunction for linear/DD motor
В	F	Multifunction for rotary motor
(EtherCAT)	М	Multifunction for linear/DD motor

			Motor			Driver					
N	Motor series	Power supply	Output	Part No. Note)1 Special Order Product	Rating/ Spec. (page)	A6SF series Multifunction type (Pulse, analog, full-closed)	A6NF series Realtime Express Network Multifunction type (full-closed)	A6BF series EtherCAT open network Multifunction type (full-closed) Special Order Product	Frame	Power capacity (at rated load) (kVA)	
			1.0 kW	MSMF104⊜1□△M	7					Approx. 2.4	
			1.5 kW	MSMF154○1□△M	7	MDDLT64SF	MDDLT64NF	MDDLT64BF	D-frame	Approx. 2.9	
Low	MSMF	3-phase	2.0 kW	MSMF204⊜1□△M	7	MEDLT84SF	MEDLT84NF	MEDLT84BF	E-frame	Approx. 3.8	
Low inertia	type 3000 r/min	400 V	3.0 kW	MSMF304○1□△M	8	MFDLTA4SF	MFDLTA4NF	MFDLTA4BF		Approx. 5.2	
ω			4.0 kW	MSMF404○1□△M	8	MEDITRACE	MEDITRANE	MEDITO (DE	F-frame	. 70	
			5.0 kW	MSMF504○1□△M	8	MFDLTB4SF	MFDLTB4NF	MFDLTB4BF		Approx. 7.8	
			1.0 kW	MDMF104○1□△M	9	MDDLT54SF	MDDLT54NF	MDDLT54BF	- D-frame	Approx. 2.4	
			1.5 kW	MDMF154○1□△M	9	MDDLT64SF	MDDLT64NF	MDDLT64BF	D-trame	Approx. 2.9	
	MDMF type 2000 r/min		3-phase	2.0 kW	MDMF204⊜1□△M	9	MEDLT84SF	MEDLT84NF	MEDLT84BF	E-frame	Approx. 3.8
			3.0 kW	MDMF304⊜1□△M	10	MFDLTA4SF	MFDLTA4NF	MFDLTA4BF		Approx. 5.2	
<			4.0 kW	MDMF404⊜1□△M	10	MFDLTB4SF	MFDLTB4NF	F-fram MFDLTB4BF	F-frame	A 7.0	
iddle			5.0 kW	MDMF504⊜1□△M	10	WIFDLI B43F	IVIFUL I B4INF	MFDLI B4BF		Approx. 7.8	
Middle inertia			0.85 kW	MGMF094⊜1□△M	11	MDDLT54SF	MDDLT54NF	MDDLT54BF	D-frame	Approx. 2.4	
₾,			1.3 kW	MGMF134○1□△M	11	MDDLT64SF	MDDLT64NF	MDDLT64BF	D-ilaille	Approx. 2.9	
	MGMF	3-phase	1.8 kW	MGMF184○1□△M	11	MEDLT84SF	MEDLT84NF	MEDLT84BF	E-frame	Approx. 3.8	
	1500 r/min	type 400 V	2.4 kW	MGMF244⊜1□△M	12	MFDLTA4SF	MFDLTA4NF	MFDLTA4BF		Approx. 5.2	
			2.9 kW	MGMF294○1□△M	12	— MFDLTB4SF MFI	MFDLTB4NF	F-frame MFDLTB4BF	F-frame	Approx. 7.8	
			4.4 kW	MGMF444○1□△M	12		MITDELDHINE	WIF DET D4DF		Арргох. 7.0	
			200 W	MHMF024○1□△M	13	- MDDLT44SF	MDDLT44NF	MDDLT44BF		Approx. 1.8	
			400 W	MHMF044○1□△M	13	IVIDDL1443F	MIDDE1 44INF		D-frame	Αμμισχ. 1.0	
			750 W	MHMF084○1□△M	13	MDDLT54SF	MDDLT54NF	MDDLT54BF	D-II aille	Approx. 2.4	
_			1000 W	MHMF094○1□△M	14	MDDLT64SF	MDDLT64NF	MDDLT64BF		Approx. 2.9	
High inertia	MHMF type	3-phase	1.0 kW	MHMF104○1□△M	14	MDDLT54SF	MDDLT54NF	MDDLT54BF	D-frame	Approx. 2.4	
nertia	2000 r/min	400 V	1.5 kW	MHMF154⊜1□△M	14	MDDLT64SF	MDDLT64NF	MDDLT64BF	D-iiailie	Approx. 2.9	
			2.0 kW	MHMF204⊜1□△M	15	MEDLT84SF	MEDLT84NF	MEDLT84BF	E-frame	Approx. 3.8	
			3.0 kW	MHMF304⊜1□△M	15	MFDLTA4SF	MFDLTA4NF	MFDLTA4BF		Approx. 5.2	
			4.0 kW	MHMF404⊜1□△M	15	MFDLTB4SF	MFDLTB4NF	MFDLTB4BF	F-frame	Approx. 7.8	
			5.0 kW	MHMF504⊜1□△M	16	IVII DEI D43F	MILDEIDHME	IVII DETD4DE		Αμριύχ. 7.0	

<sup>•</sup> Please refer to the A6BF series specifications homepage.

· Please contact us for more information

# **Specifications**

			1.0 kW	1.5 kW	2.0 kW
			AC400 V	AC400 V	AC400 V
Motor model *1			MSMF104⊜1□△M	MSMF154⊜1□△M	MSMF204⊜1□△M
Applicable	Model No.	Multifunction type	MDDLT64●F	MDDLT64●F	MEDLT84●F
driver*2	Frame sym	nbol	D-frame	D-frame	E-frame
Power sup	ply capacity	(kVA)	2.4	2.9	3.8
Rated outp	out	(W)	1000	1500	2000
Rated torq	ue	(N·m)	3.18	4.77	6.37
Continuous	s stall torque	e (N·m)	3.82	5.73	7.64
Max. torqu	е	(N·m)	9.55	14.3	19.1
Rated curr	ent	(A(rms))	3.3	4.2	5.7
Max. curre	nt	(A(o-p))	14	17.5	24
Rated spe	ed	(r/min)	3000	3000	3000
Max. spee	d	(r/min)	5500	5500	5500
Rotor inert	ia	Without brake	2.15	3.10	4.06
(×10 <sup>-4</sup> kg⋅r	m²)	With brake	2.47	3.45	4.41
Recommended moment of inertia ratio of the load and the rotor Note)1			15 times or less	15 times or less	15 times or less
Rotary end	oder specifi	cations*3	23-bit Absolute	23-bit Absolute	23-bit Absolute
	Resolutio	n per single turn	8388608	8388608	8388608

# • Brake specifications (For details, refer to P.24)

(This brake will be released when it is energized. Do not use this for braking the motor in motion.)


Static friction torque (N·m)	8.0 or more	8.0 or more	8.0 or more
Armature pull in time (ms)	50 or less	50 or less	50 or less
Armature release time (ms) Note)2	15 or less	15 or less	15 or less
Exciting current (at DC24 V) (A)	0.81±10 %	0.81±10 %	0.81±10 %
Releasing voltage (DC) (V)	2 or more	2 or more	2 or more
Exciting voltage (DC) (V)	24±2.4	24±2.4	24±2.4

## • Permissible load (For details, refer to P.23)

When assembling	Radial load (N)	980	980	980
	Thrust load Direction A (N)	588	588	588
assembling	Thrust load Direction B (N)	686	686	686
When	Radial load (N)	490	490	490
operating	Thrust load A, B-direction (N)	196	196	196

- For details of Note)1 and Note)2, refer to P.23.
- Dimensions of Motor, refer to P.17.
- \*1  $\bigcirc$   $\triangle$ : Represents the motor specifications. (refer to "Model designation" P.4.)
- \*2 : Represents the driver specifications. (refer to "Model designation" P.4.)
- \*3 When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

# Torque characteristics (at AC400 V of power voltage < Dotted line represents the torque at 10 % less supply voltage.>)



<Cautions> Reduce the moment of inertia ratio if high speed response operation is required.

Dimensions are subject to change without notice. Contact us or a dealer for the latest information.

Read the Instruction Manual carefully and understand all precautions and remarks before using the products.

Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

# **Specifications**

Special Order

			3.0 kW	4.0 kW	5.0 kW
			AC400 V	AC400 V	AC400 V
Motor model*1			MSMF304○1□△M	MSMF404⊜1□△M	MSMF504⊜1□△M
Applicable	Model No.	Multifunction type	MFDLTA4●F	MFDLTB4●F	MFDLTB4●F
driver*2	Frame syr	nbol	F-frame	F-frame	F-frame
Power sup	ply capacity	y (kVA)	5.2	7.8	7.8
Rated outp	ut	(W)	3000	4000	5000
Rated torq	ue	(N·m)	9.55	12.7	15.9
Continuous	s stall torqu	ie (N·m)	11.0	15.3	19.1
Max. torqu	е	(N·m)	28.7	38.2	47.8
Rated curr	ent	(A(rms))	9.2	9.9	12.0
Max. curre	nt	(A(o-p))	38.5	42.7	53.6
Rated spee	ed	(r/min)	3000	3000	3000
Max. spee	d	(r/min)	5500	5000	5000
Rotor inert	a	Without brake	7.04	14.4	19.0
(×10 <sup>-4</sup> kg⋅r	n²)	With brake	7.38	15.6	20.2
Recommended moment of inertia ratio of the load and the rotor Note)1			15 times or less	15 times or less	15 times or less
Rotary end	ry encoder specifications *3		23-bit Absolute	23-bit Absolute	23-bit Absolute
	Resolution	on per single turn	8388608	8388608	8388608

#### • Brake specifications (For details, refer to P.24)

(This brake will be released when it is energized. Do not use this for braking the motor in motion.)


Static friction torque (N·m)	12.0 or more	16.2 or more	22.0 or more
Armature pull in time (ms)	80 or less	110 or less	110 or less
Armature release time (ms) Note)2	15 or less	50 or less	50 or less
Exciting current (at DC24 V) (A)	0.81±10 %	0.90±10 %	0.90±10 %
Releasing voltage (DC) (V)	2 or more	2 or more	2 or more
Exciting voltage (DC) (V)	24±2.4	24±2.4	24±2.4

## • Permissible load (For details, refer to P.23)

When assembling	Radial load (N)	980	980	980
	Thrust load Direction A (N)	588	588	588
	Thrust load Direction B (N)	686	686	686
When	Radial load (N)	490	784	784
operating	Thrust load A, B-direction (N)	196	343	343

- For details of Note)1 and Note)2, refer to P.23.
- Dimensions of Motor, refer to P.17.
- \*1 \(\subseteq \subseteq \cdot\): Represents the motor specifications. (refer to "Model designation" P.4.)
- \*2 : Represents the driver specifications. (refer to "Model designation" P.4.)
- \*3 When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

# Torque characteristics (at AC400 V of power voltage < Dotted line represents the torque at 10 % less supply voltage.>)



**<Cautions>** Reduce the moment of inertia ratio if high speed response operation is required.

Dimensions are subject to change without notice. Contact us or a dealer for the latest information.

Read the Instruction Manual carefully and understand all precautions and remarks before using the products.

Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

# **Specifications**

			1.0 kW	1.5 kW	2.0 kW
			AC400 V	AC400 V	AC400 V
Motor model *1			MDMF104○1□△M	MDMF154⊜1□△M	MDMF204⊜1□△M
Applicable	Model No.	Multifunction type	MDDLT54●F	MDDLT64●F	MEDLT84●F
driver *2	Frame sym	nbol	D-frame	D-frame	E-frame
Power sup	ply capacity	(kVA)	2.4	2.9	3.8
Rated outp	out	(W)	1000	1500	2000
Rated torq	ue	(N·m)	4.77	7.16	9.55
Continuou	s stall torque	e (N·m)	5.25	7.52	10.0
Max. torqu	е	(N·m)	14.3	21.5	28.7
Rated curr	ent	(A(rms))	2.6	4.0	4.9
Max. curre	nt	(A(o-p))	11.4	17.0	21.6
Rated spe	ed	(r/min)	2000	2000	2000
Max. spee	d	(r/min)	3500	3500	3500
Rotor inert	ia	Without brake	6.18	9.16	12.1
(×10 <sup>-4</sup> kg·r	n²)	With brake	7.40	10.40	13.3
Recommended moment of inertia ratio of the load and the rotor Note)1			10 times or less	10 times or less	10 times or less
Rotary end	oder specifi	cations*3	23-bit Absolute	23-bit Absolute	23-bit Absolute
	Resolutio	n per single turn	8388608	8388608	8388608

# • Brake specifications (For details, refer to P.24)

(This brake will be released when it is energized. Do not use this for braking the motor in motion.)


Static friction torque (N·m)	13.7 or more	13.7 or more	13.7 or more
Armature pull in time (ms)	100 or less	100 or less	100 or less
Armature release time (ms) Note)2	50 or less	50 or less	50 or less
Exciting current (at DC24 V) (A)	0.79±10 %	0.79±10 %	0.79±10 %
Releasing voltage (DC) (V)	2 or more	2 or more	2 or more
Exciting voltage (DC) (V)	24±2.4	24±2.4	24±2.4

## • Permissible load (For details, refer to P.23)

When assembling	Radial load (N)	980	980	980
	Thrust load Direction A (N)	588	588	588
	Thrust load Direction B (N)	686	686	686
When	Radial load (N)	490	490	490
operating	Thrust load A, B-direction (N)	196	196	196

- For details of Note)1 and Note)2, refer to P.23.
- · Dimensions of Motor, refer to P.18.
- \*1  $\bigcirc$   $\triangle$ : Represents the motor specifications. (refer to "Model designation" P.4.)
- \*2 : Represents the driver specifications. (refer to "Model designation" P.4.)
- \*3 When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

# Torque characteristics (at AC400 V of power voltage < Dotted line represents the torque at 10 % less supply voltage.>)



<Cautions> Reduce the moment of inertia ratio if high speed response operation is required.

Dimensions are subject to change without notice. Contact us or a dealer for the latest information.

Read the Instruction Manual carefully and understand all precautions and remarks before using the products.

Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

# **Specifications**

Special Order

			3.0 kW	4.0 kW	5.0 kW
			AC400 V	AC400 V	AC400 V
Motor model*1			MDMF304○1□△M	MDMF404⊜1□△M	MDMF504⊜1□△M
Applicable	Model No.	Multifunction type	MFDLTA4●F	MFDLTB4●F	MFDLTB4●F
driver*2	Frame syr	nbol	F-frame	F-frame	F-frame
Power sup	ply capacity	y (kVA)	5.2	7.8	7.8
Rated outp	out	(W)	3000	4000	5000
Rated torq	ue	(N·m)	14.3	19.1	23.9
Continuous	s stall torqu	e (N·m)	15.0	22.0	26.3
Max. torqu	е	(N·m)	43.0	57.3	71.6
Rated curr	ent	(A(rms))	8.2	10.1	11.8
Max. curre	nt	(A(o-p))	36.4	42.5	51.0
Rated spee	ed	(r/min)	2000	2000	2000
Max. spee	d	(r/min)	3500	3500	3000
Rotor inert	ia	Without brake	18.6	46.9	58.2
(×10 <sup>-4</sup> kg⋅n	(×10 <sup>-4</sup> kg·m²) With brake		19.6	52.3	63.0
Recommended moment of inertia ratio of the load and the rotor Note)1			10 times or less	10 times or less	10 times or less
Rotary end	oder speci	fications *3	23-bit Absolute	23-bit Absolute	23-bit Absolute
	Resolution	on per single turn	8388608	8388608	8388608

# • Brake specifications (For details, refer to P.24)

(This brake will be released when it is energized. Do not use this for braking the motor in motion.)


Static friction torque (N·m)	22.0 or more	25.0 or more	44.1 or more
Armature pull in time (ms)	110 or less	80 or less	150 or less
Armature release time (ms) Note)2	50 or less	25 or less	30 or less
Exciting current (at DC24 V) (A)	0.90±10 %	1.29±10 %	1.29±10 %
Releasing voltage (DC) (V)	2 or more	2 or more	2 or more
Exciting voltage (DC) (V)	24±2.4	24±2.4	24±2.4

# • Permissible load (For details, refer to P.23)

Whon	Radial load (N)	980	1666	1666
When assembling	Thrust load Direction A (N)	588	784	784
assembling	Thrust load Direction B (N)	686	980	980
When	Radial load (N)	784	784	784
operating	Thrust load A, B-direction (N)	343	343	343

- For details of Note)1 and Note)2, refer to P.23.
- Dimensions of Motor, refer to P.18.
- \*1 \(\subseteq \subseteq \cdot\): Represents the motor specifications. (refer to "Model designation" P.4.)
- \*2 : Represents the driver specifications. (refer to "Model designation" P.4.)
- \*3 When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

# Torque characteristics (at AC400 V of power voltage < Dotted line represents the torque at 10 % less supply voltage.>)



**<Cautions>** Reduce the moment of inertia ratio if high speed response operation is required.

Dimensions are subject to change without notice. Contact us or a dealer for the latest information.

Read the Instruction Manual carefully and understand all precautions and remarks before using the products.

Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

# **Specifications**

			0.85 kW	1.3 kW	1.8 kW
			AC400 V	AC400 V	AC400 V
Motor model <sup>*1</sup>			MGMF094⊜1□△M	MGMF134○1□△M	MGMF184○1□△M
Applicable	Model No.	Multifunction type	MDDLT54●F	MDDLT64●F	MEDLT84●F
driver *2	Frame syr	nbol	D-frame	D-frame	E-frame
Power sup	ply capacit	y (kVA)	2.4	2.9	3.8
Rated outp	out	(W)	850	1300	1800
Rated torq	ue	(N·m)	5.41	8.28	11.5
Continuous	s stall torqu	e (N·m)	5.41	8.28	11.5
Max. torqu	е	(N·m)	14.3	23.3	28.8
Rated curr	ent	(A(rms))	3.0	4.8	5.9
Max. curre	nt	(A(o-p))	11.0	18.5	21.0
Rated spee	ed	(r/min)	1500	1500	1500
Max. spee	d	(r/min)	3500	3500	3500
Rotor inert	ia	Without brake	6.18	9.16	12.1
(×10 <sup>-4</sup> kg⋅r	n²)	With brake	7.40	10.4	13.3
Recommended moment of inertia ratio of the load and the rotor Note)1			10 times or less	10 times or less	10 times or less
Rotary end	oder speci	fications <sup>⁺3</sup>	23-bit Absolute	23-bit Absolute	23-bit Absolute
	Resolution	on per single turn	8388608	8388608	8388608

# • Brake specifications (For details, refer to P.24)

(This brake will be released when it is energized. Do not use this for braking the motor in motion.)


Static friction torque (N·m)	13.7 or more	13.7 or more	13.7 or more
Armature pull in time (ms)	100 or less	100 or less	100 or less
Armature release time (ms) Note)2	50 or less	50 or less	50 or less
Exciting current (at DC24 V) (A)	0.79±10 %	0.79±10 %	0.79±10 %
Releasing voltage (DC) (V)	2 or more	2 or more	2 or more
Exciting voltage (DC) (V)	24±2.4	24±2.4	24±2.4

## • Permissible load (For details, refer to P.23)

When assembling	Radial load (N)	980	980	980
	Thrust load Direction A (N)	588	588	588
	Thrust load Direction B (N)	686	686	686
When	Radial load (N)	686	686	686
operating	Thrust load A, B-direction (N)	196	196	196

- For details of Note)1 and Note)2, refer to P.23.
- Dimensions of Motor, refer to P.19.
- \*1  $\bigcirc$   $\triangle$ : Represents the motor specifications. (refer to "Model designation" P.4.)
- \*2 : Represents the driver specifications. (refer to "Model designation" P.4.)
- \*3 When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

# Torque characteristics (at AC400 V of power voltage < Dotted line represents the torque at 10 % less supply voltage.>)



<Cautions> Reduce the moment of inertia ratio if high speed response operation is required.

Dimensions are subject to change without notice. Contact us or a dealer for the latest information.

Read the Instruction Manual carefully and understand all precautions and remarks before using the products.

Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

# **Specifications**

Special Order

			2.4 kW	2.9 kW	4.4 kW
			AC400 V	AC400 V	AC400 V
Motor model *1			MGMF244○1□△M	MGMF294⊜1□△M	MGMF444○1□△M
Applicable	Model No.	Multifunction type	MFDLTA4●F	MFDLTB4●F	MFDLTB4●F
driver*2	Frame syr	nbol	F-frame	F-frame	F-frame
Power sup	ply capacity	(kVA)	5.2	5.2	7.8
Rated outp	out	(W)	2400	2900	4400
Rated torq	ue	(N·m)	15.3	18.5	28.0
Continuous	s stall torqu	e (N·m)	15.3	18.5	28.0
Max. torqu	е	(N·m)	45.8	55.4	70.0
Rated curr	ent	(A(rms))	8.0	9.7	13.8
Max. curre	nt	(A(o-p))	34.0	41.0	48.0
Rated spee	ed	(r/min)	1500	1500	1500
Max. speed	d	(r/min)	3000	3500	3000
Rotor inert	ia	Without brake	46.9	46.9	58.2
(×10 <sup>-4</sup> kg·m²) With brake		With brake	52.3	52.3	63.0
Recommended moment of inertia ratio of the load and the rotor Note)1			10 times or less	10 times or less	10 times or less
Rotary end	oder specif	ications *3	23-bit Absolute	23-bit Absolute	23-bit Absolute
	Resolution	on per single turn	8388608	8388608	8388608

#### • Brake specifications (For details, refer to P.24)

(This brake will be released when it is energized. Do not use this for braking the motor in motion.)


Static friction torque (N·m)	25.0 or more	25.0 or more	44.1 or more
Armature pull in time (ms)	80 or less	80 or less	150 or less
Armature release time (ms) Note)2	25 or less	25 or less	30 or less
Exciting current (at DC24 V) (A)	1.29±10 %	1.29±10 %	1.29±10 %
Releasing voltage (DC) (V)	2 or more	2 or more	2 or more
Exciting voltage (DC) (V)	24±2.4	24±2.4	24±2.4

# • Permissible load (For details, refer to P.23)

When	Radial load (N)	1666	1666	1666		
	Thrust load Direction A (N)	784	784	784		
	Thrust load Direction B (N)	980	980	980		
When	Radial load (N)	1176	1176	1470		
operating	Thrust load A, B-direction (N)	490	490	490		

- For details of Note)1 and Note)2, refer to P.23.
- Dimensions of Motor, refer to P.19.
- \*1 \(\subseteq \subseteq \cdot\): Represents the motor specifications. (refer to "Model designation" P.4.)
- \*2 : Represents the driver specifications. (refer to "Model designation" P.4.)
- \*3 When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

# Torque characteristics (at AC400 V of power voltage < Dotted line represents the torque at 10 % less supply voltage.>)



**<Cautions>** Reduce the moment of inertia ratio if high speed response operation is required.

Dimensions are subject to change without notice. Contact us or a dealer for the latest information.

Read the Instruction Manual carefully and understand all precautions and remarks before using the products.

Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

# **Specifications**

			200 W	400 W	750 W
			AC400 V	AC400 V	AC400 V
Motor model*1			MHMF024○1□△M	MHMF044⊜1□△M	MHMF084⊜1□△M
Applicable	Model No.	Multifunction type	MDDLT44●F	MDDLT44●F	MDDLT54●F
driver*2	Frame syr	nbol	D-frame	D-frame	D-frame
Power sup	ply capacity	/ (kVA)	1.8	1.8	2.4
Rated outp	out	(W)	200	400	750
Rated torq	ue	(N·m)	0.64	1.27	2.39
Continuous	s stall torqu	e (N·m)	0.76	1.40	2.86
Max. torqu	е	(N·m)	2.23	4.46	8.36
Rated curr	ent	(A(rms))	0.8	1.1	2.0
Max. curre	nt	(A(o-p))	3.8	5.3	9.8
Rated spe	ed	(r/min)	3000	3000	3000
Max. spee	d	(r/min)	6500	6500	6000
Rotor inert	ia	Without brake	0.29	0.56	1.56
(×10 <sup>-4</sup> kg⋅r	n²)	With brake	0.31	0.58	1.66
Recommended moment of inertia ratio of the load and the rotor Note)1			5 times or less	5 times or less	5 times or less
Rotary end	oder specif	ications *³	23-bit Absolute	23-bit Absolute	23-bit Absolute
	Resolution	on per single turn	8388608	8388608	8388608

# • Brake specifications (For details, refer to P.24)

(This brake will be released when it is energized. Do not use this for braking the motor in motion.)


Static friction torque (N·m)	1.6 or more	1.6 or more	3.8 or more
Armature pull in time (ms)	50 or less	50 or less	70 or less
Armature release time (ms) Note)2	20 or less	20 or less	20 or less
Exciting current (at DC24 V) (A)	0.36	0.36	0.42
Releasing voltage (DC) (V)	1 or more	1 or more	1 or more
Exciting voltage (DC) (V)	24±2.4	24±2.4	24±2.4

## • Permissible load (For details, refer to P.23)

\A/la a.a	Radial load (N)	392	392	686
When assembling	Thrust load Direction A (N)	147	147	294
assembling	Thrust load Direction B (N)	196	196	392
When	Radial load (N)	245	245	392
operating	Thrust load A, B-direction (N)	98	98	147

- For details of Note)1 and Note)2, refer to P.23.
- · Dimensions of Motor, refer to P.20, 21.
- \*1  $\bigcirc$   $\triangle$ : Represents the motor specifications. (refer to "Model designation" P.4.)
- \*2 : Represents the driver specifications. (refer to "Model designation" P.4.)
- \*3 When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

# Torque characteristics (at AC400 V of power voltage < Dotted line represents the torque at 10 % less supply voltage.>)



<Cautions> Reduce the moment of inertia ratio if high speed response operation is required.

Dimensions are subject to change without notice. Contact us or a dealer for the latest information.

Read the Instruction Manual carefully and understand all precautions and remarks before using the products.

Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

# **Specifications**

			1000 W	1.0 kW	1.5 kW
			AC400 V	AC400 V	AC400 V
Motor mode	el*1		MHMF094○1□△M	MHMF104○1□△M	MHMF154⊜1□△M
Applicable	licable Model No. Multifunction type		MDDLT64●F	MDDLT54●F	MDDLT64●F
driver*2	Frame syr	nbol	D-frame	D-frame	D-frame
Power sup	ply capacity	(kVA)	2.9	2.4	2.9
Rated outp	out	(W)	1000	1000	1500
Rated torq	Rated torque (N·m)		3.18	4.77	7.16
Continuous	Continuous stall torque (N·m)		3.34	5.25	7.52
Max. torque (N·m)		(N·m)	11.1	14.3	21.5
Rated curr	Rated current (A(rms))		2.9	2.6	4.0
Max. curre	nt	(A(o-p))	14.2	11.4	17
Rated spee	ed	(r/min)	3000	2000	2000
Max. spee	Max. speed (r/min)		6000	3500	3500
Rotor inert	ia	Without brake	2.03	22.9	33.4
(×10 <sup>-4</sup> kg·m²) With brake		With brake	2.13	24.1	34.6
Recommended moment of inertia ratio of the load and the rotor Note)1			5 times or less	5 times or less	5 times or less
Rotary end	oder specif	ications *3	23-bit Absolute	23-bit Absolute	23-bit Absolute
	Resolution	on per single turn	8388608	8388608	8388608

#### • Brake specifications (For details, refer to P.24)

(This brake will be released when it is energized. Do not use this for braking the motor in motion.)


Static friction torque (N·m)	3.8 or more	13.7 or more	13.7 or more
Armature pull in time (ms)	70 or less	100 or less	100 or less
Armature release time (ms) Note)2	20 or less	50 or less	50 or less
Exciting current (at DC24 V) (A)	0.42	0.79±10 %	0.79±10 %
Releasing voltage (DC) (V)	1 or more	2 or more	2 or more
Exciting voltage (DC) (V)	24±2.4	24±2.4	24±2.4

# • Permissible load (For details, refer to P.23)

Mhon	Radial load (N)	686	980	980
When assembling	Thrust load Direction A (N)	294	588	588
assembling	Thrust load Direction B (N)	392	686	686
When	Radial load (N)	392	490	490
operating	Thrust load A, B-direction (N)	147	196	196

- For details of Note)1 and Note)2, refer to P.23.
- Dimensions of Motor, refer to P.21, 22.
- \*1 \(\subseteq \subseteq \cdot\): Represents the motor specifications. (refer to "Model designation" P.4.)
- \*2 : Represents the driver specifications. (refer to "Model designation" P.4.)
- \*3 When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

# Torque characteristics (at AC400 V of power voltage < Dotted line represents the torque at 10 % less supply voltage.>)



<Cautions> Reduce the moment of inertia ratio if high speed response operation is required.

Dimensions are subject to change without notice. Contact us or a dealer for the latest information.

Read the Instruction Manual carefully and understand all precautions and remarks before using the products.

Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

# **Specifications**

			2.0 kW	3.0 kW	4.0 kW		
			AC400 V	AC400 V	AC400 V		
Motor mod	el <sup>*1</sup>		MHMF204○1□△M	MHMF304⊜1□△M	MHMF404⊜1□△M		
Applicable	Model No.	Multifunction type	MEDLT84●F	MFDLTA4●F	MFDLTB4●F		
driver*2	Frame sym	nbol	E-frame	F-frame	F-frame		
Power sup	ply capacity	(kVA)	3.8	5.2	7.8		
Rated outp	out	(W)	2000	3000	4000		
Rated torq	ue	(N·m)	9.55	14.3	19.1		
Continuous	Continuous stall torque (N·m)		11.5	17.2	22.0		
Max. torque (N·m)		(N·m)	28.7	43.0	57.3		
Rated curr	Rated current (A(rms))		6.4	8.5	10.1		
Max. curre	Max. current (A(o-p))		26.5	37.4	42.5		
Rated speed (r/min)		d (r/min) 2000 2000		2000	2000		
Max. spee	Max. speed (r/min)		eed (r/min) 3500		3500	3500	3500
Rotor inert	tia Without brake 55.7		85.3	104			
$(\times 10^{-4} \text{ kg} \cdot \text{m}^2)$ With brake		With brake 61.0		90.7	110		
Recommended moment of inertia ratio of the load and the rotor Note)1			5 times or less	5 times or less	5 times or less		
Rotary end	oder specifi	cations *3	23-bit Absolute	23-bit Absolute	23-bit Absolute		
	Resolutio	n per single turn	8388608	8388608	8388608		

# • Brake specifications (For details, refer to P.24)

(This brake will be released when it is energized. Do not use this for braking the motor in motion.)


Static friction torque (N·m)	25.0 or more	25.0 or more	25.0 or more
Armature pull in time (ms)	80 or less	80 or less	80 or less
Armature release time (ms) Note)2	25 or less	25 or less	25 or less
Exciting current (at DC24 V) (A)	1.29±10 %	1.29±10 %	1.29±10 %
Releasing voltage (DC) (V)	2 or more	2 or more	2 or more
Exciting voltage (DC) (V)	24±2.4	24±2.4	24±2.4

## • Permissible load (For details, refer to P.23)

\A/la a.a	Radial load (N)	1666	1666	1666
When assembling	Thrust load Direction A (N)	784	784	784
assembling	Thrust load Direction B (N)	980	980	980
When	Radial load (N)	784	784	784
operating	Thrust load A, B-direction (N)	343	343	343

- For details of Note)1 and Note)2, refer to P.23.
- · Dimensions of Motor, refer to P.22.
- \*1  $\bigcirc$   $\triangle$ : Represents the motor specifications. (refer to "Model designation" P.4.)
- \*2 : Represents the driver specifications. (refer to "Model designation" P.4.)
- \*3 When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

# Torque characteristics (at AC400 V of power voltage < Dotted line represents the torque at 10 % less supply voltage.>)



<Cautions> Reduce the moment of inertia ratio if high speed response operation is required.

Dimensions are subject to change without notice. Contact us or a dealer for the latest information.

Read the Instruction Manual carefully and understand all precautions and remarks before using the products.

Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

# **Specifications**

Special Order

			5.0 kW	
			AC400 V	
Motor model *1		MHMF504○1□△M		
Applicable	Model No.	Multifunction type	MFDLTB4●F	
driver*2	Frame syr	nbol	F-frame	
Power sup	ply capacity	y (kVA)	7.8	
Rated outp	out	(W)	5000	
Rated torq	ted torque (N·m)		23.9	
Continuous	Continuous stall torque (N·m)		26.3	
Max. torqu	Max. torque (N⋅m)		71.6	
Rated curr	ent	(A(rms))	11.8	
Max. curre	nt	(A(o-p))	51.0	
Rated spee	ed	(r/min)	2000	
Max. spee	d	(r/min)	3000	
Rotor inert	ia	Without brake	146	
(×10 <sup>-4</sup> kg⋅r	m²) With brake		151	
Recommended moment of inertia ratio of the load and the rotor Note)1		5 times or less		
Rotary end	Rotary encoder specifications *3		23-bit Absolute	
	Resolution	on per single turn	8388608	

#### • Brake specifications (For details, refer to P.24)

(This brake will be released when it is energized. Do not use this for braking the motor in motion.)


Static friction torque (N·m)	44.1 or more
Armature pull in time (ms)	150 or less
Armature release time (ms) Note)2	30 or less
Exciting current (at DC24 V) (A)	1.29±10 %
Releasing voltage (DC) (V)	2 or more
Exciting voltage (DC) (V)	24±2.4

# • Permissible load (For details, refer to P.23)

When	Radial load (N)	1666
assembling	Thrust load Direction A (N)	784
assembling	Thrust load Direction B (N)	980
When	Radial load (N)	784
operating	Thrust load A, B-direction (N)	343

- For details of Note)1 and Note)2, refer to P.23.
- · Dimensions of Motor, refer to P.22.
- \*1 \(\subseteq \subseteq \cdot\): Represents the motor specifications. (refer to "Model designation" P.4.)
- \*2 : Represents the driver specifications. (refer to "Model designation" P.4.)
- \*3 When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

# Torque characteristics (at AC400 V of power voltage < Dotted line represents the torque at 10 % less supply voltage.>)




**<Cautions>** Reduce the moment of inertia ratio if high speed response operation is required.

Dimensions are subject to change without notice. Contact us or a dealer for the latest information.

Read the Instruction Manual carefully and understand all precautions and remarks before using the products.

Please avoid the motor, or equipment containing the motor to be distributed to Japan, or other regions through Japan.

Special Order Product MSMF 1.0 kW to 5.0 kW [Low inertia]



Panasonic Industry Co., Ltd. | 18

Motor	output (kW)		1.0	1.5	2.0	3.0	4.0	5.0
Motor	tor model		MDMF104 ○1□△M	MDMF154 ○1□△M	MDMF204 ○1□△M	MDMF304 ○1□△M	MDMF404 ○1□△M	MDMF504 ○1□△M
	00 64	Without Brake	121	135	149	177	163	178
	23-bit	With Brake	149	163	177	205	192	207
LL	23-bit	Without Brake	127.5	141.5	155.5	183.5	169.5	184.5
	Batteryless	With Brake	155.5	169.5	183.5	211.5	195.5	213.5
LR			55	55	55	65	70	70
S			22	22	22	24	35	35
LA			145	145	145	145	200	200
LB			110	110	110	110	114.3	114.3
LC			130	130	130	130	176	176
LD			165	165	165	165	233	233
LE			6	6	6	6	3.2	3.2
LF			12	12	12	12	18	18
LG			81.3	81.3	81.3	81.3	81.3	81.3
LH			106.5	106.5	106.5	106.5	129.8	129.8
LM		Without Brake	77	91	105	133	119	134
LIVI		With Brake	105	119	133	161	148	163
LX	23-bit		44	44	44	44	44	44
LA	23-bit Batteryl	less	50.5	50.5	50.5	50.5	50.5	50.5
LZ			9	9	9	9	13.5	13.5
KB1			53	67	81	109	94	109
KB2		Without Brake	104	118	132	160	146	161
NDZ		With Brake	132	146	160	188	175	190
		LW	45	45	45	55	55	55
		LK	41	41	41	51	50	50
Key w	ay dimensions	KW	8	8	8	8	10	10
		KH	7	7	7	7	8	8
		RH	18	18	18	20	30	30
Mass	(kg)	Without Brake	4.6	5.7	6.9	9.3	13.4	15.6
iviass	(NB)	With Brake	6.1	7.2	8.4	10.9	16.8	19.0
Angle	d receptacle	23-bit	AGC047N00	00050A000(T	E Connectivit	y Ltd.) or equi	valent model	
for en	coder	23-bit Batteryless	AGC047N00	00050A000(T	E Connectivit	y Ltd.) or equi	valent model	
Analo	d receptacle for	motor	RGC106N00	001100000/T	F Connectivity	/ Ltd.) or equi	valent model	


 $\bigcirc \Box \triangle$  in the motor model number represents the motor specifications. Please refer to "[Motor] Model Designation" in P.4.


(36.2)  Key way dimensions (Key way, center tap shaft)  Angled receptacle for encoder
---

[Unit: mm]

Motor output (kW)			1.0	1.5	2.0	3.0	4.0	5.0
Motor model			MSMF104 ○1□△M	MSMF154 ○1□△M	MSMF204 ○1□△M	MSMF304 ○1□△M	MSMF404 ○1□△M	MSMF504 ○1□△M
	00 6:4	Without Brake	139	157.5	176.5	188	207	242
	23-bit	With Brake	166	184.5	203.5	213	235	270
LL	23-bit	Without Brake	145.5	164	183	194.5	213.5	248.5
	Batteryless	With Brake	172.5	191	210	219.5	241.5	276.5
LR			55	55	55	55	65	65
S			19	19	19	22	24	24
LA			115	115	115	145	145	145
LB			95	95	95	110	110	110
LC			100	100	100	120	130	130
LD			135	135	135	162	165	165
LE		3	3	3	3	6	6	
LF		10	10	10	12	12	12	
LG		81.3	81.3	81.3	81.3	81.3	81.3	
LH			101.2	101.2	101.2	101.5	106.5	106.5
1.84		Without Brake	95	113.5	132.5	144	163	198
LM		With Brake	122	140.5	159.5	169	191	226
LV	23-bit		44	44	44	44	44	44
LX	LX 23-bit Batteryless		50.5	50.5	50.5	50.5	50.5	50.5
LZ			9	9	9	9	9	9
KB1			62	80.5	99.5	121	139	174
KDO		Without Brake	122	140.5	159.5	171	190	225
KB2		With Brake	149	167.5	186.5	196	218	253
		LW	45	45	45	45	55	55
LK		LK	42	42	42	41	51	51
Key way dimensions		KW	6	6	6	8	8	8
		KH	6	6	6	7	7	7
RH		RH	15.5	15.5	15.5	18	20	20
Mana (Isra) Without Brake		Without Brake	3.6	4.6	5.6	8.7	11.5	14.5
Mass (kg) With Brake		4.7	5.6	6.6	9.9	13.2	16.1	
Angle	d receptacle	23-bit	AGC047N00	00050A000(T	E Connectivit	y Ltd.) or equi	valent model	
_	coder	23-bit Batteryless	AGC047N00	00050A000(T	E Connectivit	y Ltd.) or equi	valent model	
Angle	d receptacle for	motor	BGC106N00	001100000(T	E Connectivity	/ Ltd.) or equiv	valent model	

 $\bigcirc$   $\square$  in the motor model number represents the motor specifications. Please refer to "[Motor] Model Designation" in P.4.






1 1:4.	mml

Motor output (kW)		0.85	1.3	1.8	2.4	2.9	4.4	
Motor model		MGMF094 ○1□△M	MGMF134 ○1□△M	MGMF184 ○1□△M	MGMF244 ○1□△M	MGMF294 ○1□△M	MGMF444 ○1□△M	
	00 64	Without Brake	121	135	149	163	163	178
	23-bit	With Brake	149	163	177	192	192	207
LL	23-bit	Without Brake	127.5	141.5	155.5	169.5	169.5	184.5
	Batteryless	With Brake	155.5	169.5	183.5	198.5	198.5	213.5
LR			55	55	55	70	70	70
S			22	22	22	35	35	35
LA			145	145	145	200	200	200
LB			110	110	110	114.3	114.3	114.3
LC			130	130	130	176	176	176
LD			165	165	165	233	233	233
LE			6	6	6	3.2	3.2	3.2
LF	LF		12	12	12	18	18	18
LG	LG		81.3	81.3	81.3	81.3	81.3	81.3
LH			106.5	106.5	106.5	129.8	129.8	129.8
LM		Without Brake	77	91	105	119	119	134
LIVI		With Brake	105	119	133	148	148	163
LX	23-bit		44	44	44	44	44	44
LA	23-bit Battery	ess	50.5	50.5	50.5	50.5	50.5	50.5
LZ			9	9	9	13.5	13.5	13.5
KB1			53	67	81	94	94	109
KB2		Without Brake	104	118	132	146	146	161
NDZ		With Brake	132	146	160	175	175	190
		LW	45	45	45	55	55	55
		LK	41	41	41	50	50	50
Key w	ay dimensions	KW	8	8	8	10	10	10
		KH	7	7	7	8	8	8
		RH	18	18	18	30	30	30
Mass	(kg)	Without Brake	4.6	5.7	6.9	13.4	13.4	15.6
iviass	Mass (kg)  With Brake		6.1	7.2	8.4	16.8	16.8	19.0
Angled	d receptacle	23-bit	AGC047N00	00050A000(T	E Connectivity	y Ltd.) or equi	valent model	
for end	coder	23-bit Batteryless	AGC047N00	00050A000(T	E Connectivity	y Ltd.) or equi	valent model	
Angled	d receptacle for	motor	BGC106N00	001100000(T	E Connectivity	/ Ltd.) or equiv	alent model	

 $<sup>\</sup>bigcirc \Box \triangle$  in the motor model number represents the motor specifications.

Please refer to "[Motor] Model Designation" in P.4.




[Unit: mm]

Motor	routput (W)		200	400	
Motor model			MHMF024○1□9M	MHMF044○1□9M	
23-bit		Without Brake 85.8		102.8	
LL	23-011	With Brake	115.3	132.3	
LL	23-bit	Without Brake	85.8	102.8	
	Batteryless	With Brake	115.3	132.3	
LR			30	30	
S			11	14	
LA			70 ±0.2	70 ±0.2	
LB			50	50	
LC			60	60	
LE			3	3	
LF			6.5	6.5	
LG			71.3	71.3	
LH			75.3	75.3	
LM		Without Brake	59.5	76.5	
LIVI		With Brake	89	106	
LX	23-bit		26.3	26.3	
LA	23-bit Batteryl	ess	26.3	26.3	
LZ			4.5	4.5	
KB1			42.7	59.7	
KB2		Without Brake	71.5	88.5	
ND2		With Brake	101	118	
		LW	20	25	
		LK	18	22.5	
Key w	vay dimensions	KW	4	5	
		KH	4	5	
		RH	8.5	11	
Mass (kg)		Without Brake	1.0	1.4	
iviass	(KB)	With Brake	1.4	1.8	
Angle	ed receptacle	23-bit	AGC047N0000050A000(TE Connectivity	y Ltd.) or equivalent model	
	coder	23-bit Batteryless	AGC047N0000050A000(TE Connectivity	y Ltd.) or equivalent model	
Anale	ed receptacle for	motor	BGC863N000051A000(TE Connectivity	Ltd.) or equivalent model	

 $<sup>\</sup>bigcirc$  in the motor model number represents the motor specifications.

Please refer to "[Motor] Model Designation" in P.4.




[Unit: mm]

Motor model         MHMF084 1 □9M         MHMF094 1 □9M           MHMF084 1 □9M         MHMF094 1 □9M           MHMF094 1 □9M         MHMF094 1 □9M           L2.7           With Brake         109.9         122.7           Batteryless         156.3           LR         35         35         35           Say         19         10         10         10         10         10	Motor out	nut (W)		750	1000
LL		. , ,			
LL         With Brake         143.5         156.3           23-bit Batteryless         With Brake         109.9         122.7           S         35         35         35           S         19         19         19           LA         90 ±0.2         90 ±0.2         90 ±0.2           LB         70         70         70           LC         80         80         80           LE         3         3         3           LF         8         8         8           LG         76.3         76.3         76.3           LH         85.3         85.3         85.3           LH         85.3         85.3         85.3           LM         With Brake         117.2         130         96.4           LX         23-bit Batteryless         26.3         26.3         26.3           LZ         6.2         6.2         6.2         6.2           KB1         56.7         78.5         78.5           KB2         Without Brake         95.6         108.4           KB2         LK         22         22           KW         6         6	00	n h:4	Without Brake	109.9	122.7
23-bit   Batteryless   Without Brake   109.9   122.7		3-DII	With Brake	143.5	156.3
LR       35       35         S       19       19         LA       90 ±0.2       90 ±0.2         LB       70       70         LC       80       80         LE       3       3         LF       8       8         LG       76.3       76.3         LH       85.3       85.3         LH       85.3       85.3         LM       Without Brake       83.6       96.4         With Brake       117.2       130         LX       23-bit Batteryles       26.3       26.3         LZ       6.2       6.2         KB1       65.7       78.5         KB2       Without Brake       95.6       108.4         With Brake       129.2       142         LK       25       25         LK       22       22         Key way dimensions       KW       6       6         KH       6       6         RH       15.5       15.5         Without Brake       24       28	23	3-bit	Without Brake	109.9	122.7
S     19     19       LA     90 ±0.2     90 ±0.2       LB     70     70       LC     80     80       LE     3     3       LF     8     8       LG     76.3     76.3       LH     85.3     85.3       LH     85.3     85.3       LM     Without Brake     83.6     96.4       With Brake     117.2     130       LX     23-bit Batteryles     26.3     26.3       LZ     6.2     6.2       KB1     65.7     78.5       KB2     Without Brake     95.6     108.4       With Brake     129.2     142       LK     22     25       LK     22     22       Key way dimensions     KW     6     6       KH     6     6       RH     15.5     15.5       Without Brake     24     28	Ba	atteryless	With Brake	143.5	156.3
LA       90 ±0.2       90 ±0.2         LB       70       70         LC       80       80         LE       3       3         LF       8       8         LG       76.3       76.3         LH       85.3       85.3         LM       Without Brake       83.6       96.4         With Brake       117.2       130         LX       23-bit       26.3       26.3         LZ       6.2       6.2         KB1       65.7       78.5         KB2       Without Brake       95.6       108.4         With Brake       129.2       142         LK       25       25         LK       22       22         Key way dimensions       KW       6       6         KH       6       6         RH       15.5       15.5         Without Brake       2.4       2.8	LR			35	35
LB     70     70       LC     80     80       LE     3     3       LF     8     8       LG     76.3     76.3       LH     85.3     85.3       LM     Without Brake     83.6     96.4       With Brake     117.2     130       LX     23-bit     26.3     26.3       LZ     6.2     6.2       KB1     65.7     78.5       KB2     Without Brake     95.6     108.4       With Brake     129.2     142       LW     25     25       LK     22     22       Key way dimensions     KW     6     6       KH     6     6       RH     15.5     15.5       Without Brake     2.4     2.8	S			19	19
LC     80     80       LE     3     3       LF     8     8       LG     76.3     76.3       LH     85.3     85.3       LM     Without Brake     83.6     96.4       With Brake     117.2     130       LX     23-bit     26.3     26.3       LZ     23-bit Batteryless     26.3     26.3       LZ     6.2     6.2       KB1     65.7     78.5       KB2     Without Brake     95.6     108.4       With Brake     129.2     142       LK     25     25       LK     22     22       KW     6     6       KH     6     6       RH     15.5     15.5       Without Brake     2.4     2.8	LA			90 ±0.2	90 ±0.2
LE       3       3         LF       8       8         LG       76.3       76.3         LH       85.3       85.3         LM       Without Brake       83.6       96.4         With Brake       117.2       130         LX       23-bit       26.3       26.3         LZ       6.2       6.2         KB1       65.7       78.5         KB2       Without Brake       95.6       108.4         With Brake       129.2       142         LW       25       25         LK       22       22         KW       6       6         KH       6       6         RH       15.5       15.5         Without Brake       2.4       2.8	LB			70	70
LF       8       8         LG       76.3       76.3         LH       85.3       85.3         LM       Without Brake       83.6       96.4         With Brake       117.2       130         LX       23-bit       26.3       26.3         LZ       6.2       6.2         KB1       65.7       78.5         KB2       Without Brake       95.6       108.4         With Brake       129.2       142         Key way dimensions       KW       6       6         KW       6       6         KH       6       6         RH       15.5       15.5         Without Brake       2.4       2.8	LC			80	80
LG       76.3       76.3         LH       85.3       85.3         LM       Without Brake       83.6       96.4         With Brake       117.2       130         LX       23-bit Batteryless       26.3       26.3         LZ       6.2       6.2         KB1       65.7       78.5         KB2       Without Brake       95.6       108.4         With Brake       129.2       142         Key way dimensions       KW       6       6         KH       6       6         RH       15.5       15.5         Without Brake       2.4       2.8	LE			3	3
LH     85.3     85.3       LM     Without Brake     83.6     96.4       With Brake     117.2     130       LX     23-bit     26.3     26.3       LZ     6.2     6.2       KB1     65.7     78.5       KB2     Without Brake     95.6     108.4       With Brake     129.2     142       LW     25     25       LK     22     22       Key way dimensions     KW     6     6       KH     6     6       RH     15.5     15.5       Without Brake     2.4     2.8	LF			8	8
LM       Without Brake       83.6       96.4         With Brake       117.2       130         LX       23-bit       26.3       26.3         23-bit Batteryless       26.3       26.3         LZ       6.2       6.2         KB1       65.7       78.5         KB2       Without Brake       95.6       108.4         With Brake       129.2       142         LW       25       25         LK       22       22         KW       6       6         KH       6       6         RH       15.5       15.5         Without Brake       2.4       2.8	LG	LG		76.3	76.3
LM     With Brake     117.2     130       LX     23-bit     26.3     26.3       23-bit Batteryless     26.3     26.3       LZ     6.2     6.2       KB1     65.7     78.5       KB2     Without Brake     95.6     108.4       With Brake     129.2     142       LW     25     25       LK     22     22       KW     6     6       KH     6     6       RH     15.5     15.5       Without Brake     2.4     2.8	LH	LH		85.3	85.3
With Brake   117.2   130	1.04		Without Brake	83.6	96.4
Z3-bit Batteryless   Z6.3   Z6.2   Z6.2   Z6.2   Z6.2   Z6.2   Z6.2   Z6.2   Z6.2   Z6.3   Z6.3	LIVI		With Brake	117.2	130
23-bit Batteryless   26.3   26.3	23	3-bit		26.3	26.3
KB1       65.7       78.5         KB2       Without Brake       95.6       108.4         With Brake       129.2       142         LW       25       25         LK       22       22         KW       6       6         KH       6       6         RH       15.5       15.5         Without Brake       2.4       2.8	23	3-bit Batteryl	ess	26.3	26.3
KB2       Without Brake       95.6       108.4         With Brake       129.2       142         LW       25       25         LK       22       22         KW       6       6         KH       6       6         RH       15.5       15.5         Without Brake       2.4       2.8	LZ			6.2	6.2
KB2       With Brake       129.2       142         LW       25       25         LK       22       22         KW       6       6         KH       6       6         RH       15.5       15.5         Without Brake       2.4       2.8	KB1			65.7	78.5
With Brake       129.2       142         LW       25       25         LK       22       22         KW       6       6         KH       6       6         RH       15.5       15.5         Without Brake       2.4       2.8	KDO		Without Brake	95.6	108.4
Key way dimensions     LK     22     22       KW     6     6       KH     6     6       RH     15.5     15.5       Without Brake     2.4     2.8	NB2		With Brake	129.2	142
Key way dimensions     KW     6     6       KH     6     6       RH     15.5     15.5       Without Brake     2.4     2.8			LW	25	25
KH 6 6 6 RH 15.5 15.5 Without Brake 2.4 2.8			LK	22	22
RH 15.5 15.5 Without Brake 2.4 2.8	Key way o	dimensions	KW	6	6
Without Brake 2.4 2.8	, ,		KH	6	6
Mass (kg) Without Brake 2.4 2.8			RH	15.5	15.5
Mass (KD)	NA (1 -2)		Without Brake	2.4	2.8
With Brake 3.2 3.6	iviass (Kg)	)	With Brake	3.2	3.6
Angled receptacle 23-bit AGC047N0000050A000(TE Connectivity Ltd.) or equivalent model	Angled re	ceptacle	23-bit	AGC047N0000050A000(TE Connectivity	y Ltd.) or equivalent model
for encoder 23-bit Batteryless AGC047N0000050A000(TE Connectivity Ltd.) or equivalent model			23-bit Batteryless	AGC047N0000050A000(TE Connectivity	y Ltd.) or equivalent model
Angled receptacle for motor BGC863N000051A000(TE Connectivity Ltd.) or equivalent model	Angled re	ceptacle for	motor	BGC863N000051A000(TE Connectivity	Ltd.) or equivalent model

 $<sup>\</sup>bigcirc$  in the motor model number represents the motor specifications.

Please refer to "[Motor] Model Designation" in P.4.



[Unit: mm]

Motor	output (kW)		1.0	1.5	2.0	3.0	4.0	5.0
Motor model			MHMF104 ○1□△M	MHMF154 ○1□△M	MHMF204 ○1□△M	MHMF304 ○1□△M	MHMF404 ○1□△M	MHMF504 ○1□△M
	23-bit	Without Brake	149	163	163	178	192.5	208.5
LL	23-011	With Brake	177	191	192	207	221.5	237.5
LL	23-bit	Without Brake	155.5	169.5	169.5	184.5	199	215
	Batteryless	With Brake	183.5	197.5	198.5	213.5	228	244
LR			70	70	80	80	80	80
S			22	22	35	35	35	35
LA			145	145	200	200	200	200
LB			110	110	114.3	114.3	114.3	114.3
LC			130	130	176	176	176	176
LD			165	165	233	233	233	233
LE			6	6	3.2	3.2	3.2	3.2
LF		12	12	18	18	18	18	
LG		81.3	81.3	81.3	81.3	81.3	81.3	
LH			116.2	116.2	139.2	139.2	139.2	139.2
LM		Without Brake	105	119	119	134	148.5	164.5
LIVI		With Brake	133	147	148	163	177.5	193.5
LX	23-bit		44	44	44	44	44	44
LA	23-bit Batteryl	ess	50.5	50.5	50.5	50.5	50.5	50.5
LZ			9	9	13.5	13.5	13.5	13.5
KB1			71	85	80.5	95.5	110	126
KDO		Without Brake	132	146	146	161	175.5	191.5
KB2		With Brake	160	174	175	190	204.5	220.5
		LW	45	45	55	55	55	55
LK		LK	41	41	50	50	50	50
, ,		KW	8	8	10	10	10	10
		KH	7	7	8	8	8	8
		RH	18	18	30	30	30	30
Mana (kg) With		Without Brake	6.1	7.7	11.3	13.8	16.2	19.6
Mass (kg)  With Brake		7.6	9.2	14.6	17.2	19.4	22.8	
Angled receptacle 23-bit		23-bit	AGC047N00	00050A000(T	E Connectivit	y Ltd.) or equi	valent model	
for en		23-bit Batteryless	AGC047N00	00050A000(T	E Connectivit	y Ltd.) or equi	valent model	
Angle	d receptacle for	· · · · · · · · · · · · · · · · · · ·		•	E Connectivity	· · · · · · · · · · · · · · · · · · ·		
	•			•		· · ·		

 $<sup>\</sup>bigcirc \Box \triangle$  in the motor model number represents the motor specifications.

Special Order Product MHMF 1.0 kW to 5.0 kW [High inertia]

Please refer to "[Motor] Model Designation" in P.4.

# **Environmental Conditions**

lt	em		Conditions			
Ambient ter	nperature	0 °C to 40 °C (free from freezing)				
Ambient hu	midity	20 %RH to 85 %	%RH (free from condensation)			
Storage ten	nperature	–20 °C to 65 °C	(Max.temperature guarantee: 80 °C for 72 hours free from condensation)			
Storage hur	midity	20 %RH to 85 %	%RH (free from condensation)			
		Motor unit	49 m/s² or less X,Y,Z directions But when the motor doesn't operate, 24.5 m/s² or less. (At center of frame, 20 Hz to 3000 Hz, with not more than 1.5 mm amplitude)			
Vibration *1	Motor only	Encoder connector unit and Motor connector unit	Acc. EN60068-2-6 98 m/s² X, Y, Z directions (At mounting position, with the connectors mated) Frequency: 50 Hz to 2000 Hz Frequency change speed: 1 Octave/min Test duration: 10 cycles each X, Y, Z directions			
Impact Motor only Lower than 98 m/s² (10 G)		m/s² (10 G)				
Enclosure rating	Motor only	IP67 (except ro the encoder cor	tating portion of output shaft and connecting pin part of the motor connector and nnector)			
Altitude		Lower than 100	0 m			

\*1 After mounting the device, ensure that the vibration resistance performance of the motor and connector meets the defined requirements.

# <Note>

Initial setup of rotational direction: positive = CCW and negative = CW. Pay an extra attention.




# Notes on [Motor specification] page

- Note) 1. Consult us or a dealer if the load moment of inertia exceeds the specified value.
- Note) 2. Releasing time values represent the ones with DC-cutoff using a varistor.

# **Permissible Load at Output Shaft**

The radial load is defined as a load applied to the output shaft in the right-angle direction. This load is generated when the gear head is coupled to the machine using a chain, belt, etc., but not when the gear head is directly connected to the coupling. As shown in the right figure, the permissible value is determined based on the load applied to the L/2 position of the output shaft. The thrust load is defined as a load applied to the output shaft in the axial direction.

Because the radial load and thrust load significantly affect the life of the bearing, take care not to allow the load during operation to exceed the permissible radial load and thrust load shown in the table below.



## Specifications of Built-in Holding Brake

Motor series	Motor output	Static friction torque <sup>11</sup> (N·m)	Rotary part inertia <sup>*2</sup> (10 <sup>-4</sup> kg·m²)	Armature pull in time <sup>'2</sup> (ms)	Armature release time <sup>'2</sup> (ms)	Release voltage <sup>-1</sup> (DC, V)	Exciting voltage <sup>1</sup> (DC, V)	Exciting current (at DC24 V) <sup>2</sup> (DC, A)	Allowable braking energy; 1 time each*2 (J)	All allowable braking Energy <sup>2</sup> (J)	Allowable angular acceleration*2 (rad/s²)
	1.0 kW 1.5 kW 2.0 kW	8.0 or more	0.175	50 or less	15 or less <sup>*3</sup>			0.81 ± 10 %	600	5.0 × 10⁴	
MSMF	3.0 kW	12.0 or more		80 or less		2 or more	24 ± 2.4			9.0 × 10 <sup>5</sup>	10000
	4.0 kW	16.2 or more	1.10	110 or loss	F0 or loss*3			0.90 ± 10 %	1470	2.16 × 10 <sup>6</sup>	
	5.0 kW	22.0 or more	1.12	110 or less	50 or less*3				1545	2.0 × 10 <sup>6</sup>	
	1.0 kW 1.5 kW 2.0 kW	13.7 or more	1.12	100 or less	50 or less <sup>'3</sup>			0.79 ± 10 %	1470	2.16 × 10 <sup>6</sup>	10000
MDMF	3.0 kW	22.0 or more		110 or less		2 or more	24 ± 2.4	0.90 ± 10 %	1545	2.0 × 10 <sup>6</sup>	
	4.0 kW	25.0 or more	4.7	80 or less	25 or less*3			1 00 10 0/	4000	3.0 × 10 <sup>6</sup>	5440
	5.0 kW	44.1 or more	4.1	150 or less	30 or less*3			1.29 ± 10 %	1800	3.1 × 10 <sup>6</sup>	5108
	0.85 kW 1.3 kW 1.8 kW	13.7 or more	1.12	100 or less	50 or less*3			0.79 ± 10 %	1470	2.16 × 10 <sup>6</sup>	10000
MGMF	2.4 kW 2.9 kW	25.0 or more	4.7	80 or less	25 or less <sup>*3</sup>	2 or more 24	24 ± 2.4	1.29 ± 10 %	1800	3.0 × 10 <sup>6</sup>	5440
	4.4 kW	44.1 or more	3.93	150 or less	30 or less*3					3.1 × 10 <sup>6</sup>	5108
	200 W	1.6 or more	0.018	50 or less				0.36 ± 10 %	105	44.1 × 10 <sup>3</sup>	
	400 W	1.0 01 111016	0.010	30 01 1633	20 or less*3	1 or more	24 . 2 4	0.30 ± 10 %	103	44.1 × 10	30000
	750 W	2.0 or more	0.075	70 or loop	20 01 1655	1 of more	24 ± 2.4	0.40 - 10.9/	105	90 0 10 <sup>3</sup>	30000
	1000 W	3.8 or more	0.075	70 or less				0.42 ± 10 %	185	80.0 × 10 <sup>3</sup>	
MHMF	1.0 kW 1.5 kW	13.7 or more	1.12	100 or less	50 or less*3	2 or more		0.79 ± 10 %	1470	2.16 × 10 <sup>6</sup>	10000
	2.0 kW 3.0 kW 4.0 kW	25.0 or more	4.7	80 or less	25 or less*3		24 ± 2.4	1.29 ± 10 %	1800	3.0 × 10 <sup>6</sup>	5440
	5.0 kW	44.1 or more	4.1	150 or less	30 or less*3					3.1 × 10 <sup>6</sup>	5108

<sup>\*1</sup> Value of our delivery inspection.

<sup>\*2</sup> Representative value at 20 °C.

<sup>\*3 4.1.3</sup> Surge absorber for motor brake

	Inp	ut power	Main circuit	3-phase 380 V $^{+10}_{-15}$ % to 480 V $^{+10}_{-15}$ % 50 Hz / 60 Hz TN (Ground the neutral point)
			Control circuit	DC 24 V ±15 %
			Temperature	Ambient temperature: 0 °C to 55 °C (free from freezing) Storage temperature: -20 °C to 65 °C (Max.temperature guarantee: 80 °C for 72 hours free from condensation*1)
	En	vironment	Humidity	Both operating and storage : 20 %RH to 85 %RH (free from condensation 1)
			Altitude	Lower than 1000 m
			Vibration	5.88 m/s <sup>2</sup> or less, 10 Hz to 60 Hz
	Co	ntrol method		IGBT PWM Sinusoidal wave drive
	End	coder feedback		23-bit (8388608 resolution) absolute encoder, 7-wire serial  * When using it as an incremental system (not using multi-turn data), do not connect the battery for absolute encoder. Parameter Pr. 0.15 must be set to "1" (factory settings).
	Ext	External scale feedback		A/B phase, homing signal differential input. Serial communication is also supported.  Manufacturers that support serial communication scale:  Fagor Automation S.Coop., HEIDENHAIN, Magnescale Co., Ltd., Mitutoyo Corporation  Nidec Sankyo Corporation, Renishaw plc
Basic S		Control signal	Input	General purpose 10 inputs  The function of general-purpose input is selected by parameters.
Specifications	_	Control signal	Output	General purpose 6 outputs  The function of general-purpose output is selected by parameters.
tion	iterfa	Analog signal	Input	3 inputs (16-bit A/D : 1 input, 12-bit A/D : 2 inputs)
S	е с	Analog signal	Output	2 outputs (Analog monitor: 2 output)
	Interface connector	Dulas sismal	Input	2 inputs (Photo-coupler input, Line receiver input)  Both open collector and line driver interface can be connected.  High speed line driver interface can be connected.
		Pulse signal	Output	4 outputs (Line driver: 3 output, open collector: 1 output) Line driver output for encoder pulses (A/B/Z signal) or external feedback pulses (EXA/EXB/EXZ signal) open collector output also available for Z or EXZ signal.
			USB	USB interface to connect to computers for parameter setting or status monitoring.
		mmunication ction	RS232	1:1 communication
		<b></b>	RS485	1: n communication (max 31) (Supports Modbus)
	Sat	fety function		A dedicated connector is provided for Functional Safety.
	Fro	nt panel		(1) 5 keys (2) LED (6-digit)
	Re	generation		Built-in regenerative resistor (external resistor is also enabled.)
	Dyı	namic brake		Built-in
	Co	ntrol mode		Switching among the following 7 mode is enabled, (1) Position control (2) Speed control (3) Torque control (4) Position/Speed control (5) Position/Torque control (6) Speed/Torque control (7) Full-closed control

<sup>\*1</sup> Air containing water vapor will become saturated with water vapor as the temperature falls, causing dew.

	Со	ntrol input			(1) servo-ON input (2) Alarm clear input (3) Gain switch input (4) Positive direction drive inhibit input (5) Negative direction drive inhibit input (6) Forced alarm input (7) Inertia ratio switch input
	Со	ntrol outpu	t		(1) Servo-alarm output (2) Servo-ready output (3) External brake off output (4) At-speed output (5) Torque in-limit output (6) Zero speed detection output (7) Warning output (8) Alarm clear attribute output (9) Servo on status output
		Control input			<ul> <li>(1) Deviation counter clear input (2) Command pulse inhibit input</li> <li>(3) Command division/multiplication switch input (4) Anti-vibration switch input</li> <li>(5) Torque limit switch input (6) Control mode switch input</li> </ul>
		Control or			(1) In-position output (2) Position command ON/OFF output
			Max. command	pulse frequency	500 kpps (Optocoupler interface), 8 Mpps (When using line receiver input multiplied by 4)
			Input pulse si	anal format	Differential input. Selectable by parameter.
	Р		mpat paide of	griai iorriai	([1]Positive/Negative pulse [2]A/B quadrature [3]Pulse/Direction)
	Position contro	Pulse input	Electronic gea (Division/Mult command pul	iplication of	Applicable scaling ratio: 1/1000 times to 8000 times  Any value of 1 - 2 <sup>30</sup> can be set for both numerator (which corresponds to encoder resolution) and denominator (which corresponds to command pulse resolution per motor revolution), but the combination has to be within the range shown above.
	쿰		Smoothing filt	ter	Primary delay filter or FIR type filter is adaptable to the command input
	_	Analog	Torque limit c	ommand input	Individual torque limit for both positive and negative direction is enabled.
		input Torque feed forward input		orward input	Analog voltage can be used as torque feed forward input.
		Two-degree-of-freedom control		control	Available
			tion control		Available
		Load vari	ation suppress	ion control	Available
		Block operation			Modbus (RS 232, RS 485) or interface is selectable
		·			(1) Internal command velocity selection input (2) Speed zero clamp input
		Control in	put		(3) Velocity command sign input (4) Control mode switch input
		Control output			(1) Speed coincidence output (2) Velocity command ON/OFF output
	တ		Velocity comm	nand innut	Velocity command input with analog voltage is possible. Scale setting and com-
	Speed	Analog			mand polarity vary depending on parameters. (6 V/Rated rotational speed: Default)
	ed.	input		ommand input	Individual torque limit for both positive and negative direction is enabled.
	ပ္ခ	Torque feed forward input			Analog voltage can be used as torque feed forward input.
	contro	Internal velocity command		nd	Switching the internal 8 speed is enabled by command input.
	_	Soft-start/down function			Individual setup of acceleration and deceleration is enabled,
		Coood 70	Speed zero clamp		with 0 s to 10 s/1000 r/min. Sigmoid acceleration/deceleration is also enabled.  Internal velocity command can be clamped to 0 with speed zero clamp input.
Function			Two-degree-of-freedom control		Available
豆	코	Control input		COTILIOI	Speed zero clamp input, torque command sign input, control mode switch input.
3	Torque	Control output			(1) Speed coincidence output (2) Speed in-limit output
	ē	Analog			Torque command input with analog voltage is possible. Scale setting and com-
	control	input	IOMORE COMMISSION INDITI		mand polarity vary depending on parameters. (3 V/rated torque Default)
	<u>o</u>	Speed lin	nit function		Speed limit value with parameter is enabled.
		Control input			<ul> <li>(1) Deviation counter clear input (2) Command pulse inhibit input</li> <li>(3) Command division/multiplication switch input</li> <li>(4) Anti-vibration switch input (5) Torque limit switch input</li> </ul>
		Control or	utput		(1) In-position output (2) Position command ON/OFF output
			Max. command	pulse frequency	500 kpps (Optocoupler interface), 8 Mpps (When using line receiver input multiplied by 4)
			Input pulse si	gnal format	Differential input. Selectable by parameter.
		Pulse	, , , , , , , ,		([1]Positive/Negative pulse [2]A/B quadrature [3]Pulse/Direction)
	Full-closed contro	input	Electronic gea (Division/Mult command pul	iplication of se)	Applicable scaling ratio: 1/1000 times to 8000 times  Any value of 1 - 2 30 can be set for both numerator (which corresponds to encoder resolution) and denominator (which corresponds to command pulse resolution per motor revolution), but the combination has to be within the range shown above.
	ed	A !	Smoothing filt		Primary delay filter or FIR type filter is adaptable to the command input
	8	Analog input		ommand input	Individual torque limit for both positive and negative direction is enabled.
	룿	πραι	Torque feed for	orward input	Analog voltage can be used as torque feed forward input.  1/40 times to 1280 times
	Ы		Setting range of external scale division/multiplication		Although ratio of the encoder pulse (numerator) and external scale pulse (denominator) can be arbitrarily set in the range of 1 to 2 <sup>23</sup> for the numerator and in the range of 1 to 2 <sup>23</sup> for the denominator, this product should be used within the aforementioned range.
		Two-degr	ee-of-freedom	control	Available
			tion control		Available
			ation suppress	ion control	Available
	<u> </u>	Block ope	Block operation		Modbus (RS 232, RS 485) or interface is selectable
	ဂ္ဂ	Auto tunir			The load inertia is identified in real time by the driving state of the motor operating according to the command given by the controlling device and set up support software "PANATERM". The gain is set automatically in accordance with the rigidity setting.
	l∄	Division o	f encoder feed	back pulse	Set up of any value is enabled (encoder pulses count is the max.).
	Common	Protective	e function	Hard error	Over-voltage, under-voltage, over-speed, over-load, over-heat, over-current and encoder error etc.  Excess position deviation, command pulse division error, EEPROM error etc.
		Alarm dat	a trace back	301. 01101	Tracing back of alarm data is available
1					U


			М	ain circuit	3-phase 380 V $^{+10}_{-15}$ % to 480 V $^{+10}_{-15}$ % 50 Hz / 60 Hz			
	Inp	out power			TN (Ground the neutral point)			
			Co	ntrol circuit	DC 24 V ±15 %			
			Те	mperature	Ambient temperature: 0 °C to 55 °C (free from freezing) Storage temperature: -20 °C to 65 °C (Max.temperature guarantee: 80 °C for 72 hours free from condensation 1)			
	En	vironment	ŀ	Humidity	Both operating and storage : 20 %RH to 85 %RH (free from condensation*1)			
				Altitude	Lower than 1000 m			
			\	/ibration	5.88 m/s² or less, 10 Hz to 60 Hz			
	Со	ntrol method	d		IGBT PWM Sinusoidal wave drive			
	En	coder feedb	ack		23-bit (8388608 resolution) absolute encoder, 7-wire serial  * When using it as an incremental system (not using multi-turn data), do not connect the battery for absolute encoder. Parameter Pr. 0.15 must be set to "1" (factory settings).			
	Ex	ternal scale	e feedback		A/B phase, homing signal differential input. Serial communication is also supported.  Manufacturers that support serial communication scale:  Fagor Automation S.Coop., HEIDENHAIN, Magnescale Co., Ltd., Mitutoyo Corporation  Nidec Sankyo Corporation, Renishaw plc			
Bas	Inte			Input	Each 8 input can be assigned by the parameter.			
ic Sp	Interface	Control sig	jnai	Output	Each 3 output can be assigned by the parameter.			
Basic Specifications	connector	Analog sig	ınal	Output	2 outputs for analog monitors 1 and 2			
tions	ctor	Pulse sign	al	Output	Line driver output for encoder pulses (A/B phase signal) or external scale pulses.			
				ne Express RTEX)	Communication for transmission of a real-time operation command, the parameter setting, or the status monitoring.			
	Cor	mmunication -	l	JSB	USB interface to connect to computers (setup support software PANATERM) for parameter setting or status monitoring.			
	Sa	fety termina	I		Terminal to support safety function.			
	Front panel  Regeneration			<ul><li>(1) 7 segment LED (double digits) (2) Network status LED (LINK,COM)</li><li>(3) Rotary switch for node address setting</li><li>(4) Analog monitor output (Analog monitors 1 and 2)</li></ul>				
					Built-in regenerative resistor (External regenerative resistor is also available)			
	Dy	namic brake	)		Built-in			
	Control mode				<ul> <li>(1) Semi-closed control Position control: Profile position control (PP), Cyclic position control (CP) Velocity control: Cyclic velocity control (CV) Torque control: Cyclic torque control (CT)</li> <li>(2) Full-closed control Position control: Profile position control (PP), Cyclic position control (CP)</li> <li>The two modes, [1] and [2] above are switched by parameters.</li> <li>Switch PP/CP/CV/CT mode according to the RTEX communication command.</li> </ul>			

<sup>\*1</sup> Air containing water vapor will become saturated with water vapor as the temperature falls, causing dew.

	Control input		Positive direction drive inhibit input, Negative direction drive inhibit, Latch signal, Near home position, etc					
	Control output		Positioning completion etc.					
	Position	Input mode	Command type by RTEX command					
	command input	Smoothing filter	Either a primary delay filter or a FIR type filter can be selected against command input.					
	Damping control	Officering inter	Available (Up to 3 frequency settings,out of 4 settings in total,can be used simultaneously.)					
Position			Available (2 filter available used simultaneously)					
≝:	Model type damping filter		,					
3	Feed forward fun		Available (speed/torque)					
control	Load variation suppression control		Available					
풏	Gain 3 switching		Available					
=	Quadrant glitch in	nhibit function	Available					
	Two-degree-of-fre	edom control mode	Available					
	Motor operatable	setup function	Available					
	External scale position	on information monitor	Available					
	Other available fu	ınationa	Friction torque compensation, Torque limit switching function, Torque saturation protection					
	Oli lei avallable il	arictions	function, Single-turn absolute function, Continuous rotating absolute encoder function					
	Control input		Positive direction drive inhibit input, Negative direction drive inhibit, Latch signal, etc					
	Control output		At speed etc.					
	Position		O II I DTEV					
ဟ	command input	Input mode	Command type by RTEX command  0 s to 10 s / 1000 r/min Acceleration and deceleration can be set separately.					
Speed	Soft start/slowdo	wn function	S-curve acceleration/deceleration is also available.					
S	Feed forward function		Available (torque)					
contro	Load variation suppression control		Available					
<u></u>	Two-degree-of-freedom control mode		Available (standard type)					
	External scale position information monitor		Available					
	Other available functions		Friction torque compensation, Torque limit switching function, Torque saturation protection function, Single-turn absolute function, Continuous rotating absolute encoder function					
$\vdash$	Control input		Positive direction drive inhibit input, Negative direction drive inhibit, Latch signal, etc					
ㅋ	Control output		At speed etc.					
orq	Position		At speed etc.					
Torque contro	command input Input mode		Command type by RTEX command					
Ĭ	Speed limit function		Speed limit value can be set by parameter. (Switched by RTEX command.)					
<u>o</u>		on information monitor	Available					
	Other available functions		Single-turn absolute function Continuous rotating absolute encoder function					
	Control input		Positive direction drive inhibit input, Negative direction drive inhibit, Latch signal, Near home position, etc					
	Control output		Positioning completion etc.					
	Position	Input mode	Command type by RTEX command					
	command input	Smoothing filter	Either a primary delay filter or a FIR type filter can be selected against command input.					
Full-closed control	Setting range of external scale division/multiplication.		1/40 times to 125200 times  Although the ratio of the encoder pulse (numerator) and external scale pulse (denominate can be set anywhere between the range of 1 to 2 <sup>23</sup> for the numerator and 1 to 2 <sup>23</sup> for the denominator, Please use within the range indicated above.					
sol	Damping control		Available(Up to 3 frequency settings,out of 4 settings in total,can be used simultaneously.					
be	Feed forward fun	ction	Available (op to 3 frequency settings,out of 4 settings in total,can be used simultaneously. Available (speed/torque)					
8								
랅		ppression control	Available					
2	Gain 3 switching		Available					
		uppression function	Available					
	Quadrant glitch in		Available					
		edom control mode	Available (standard type)					
	Motor operatable	setup function	Available					
	External scale position	on information monitor	Available					
L	Other available fu	unctions	Friction torque compensation, Torque limit switching function, Torque saturation protection func					
	Electronic gear ratio setting		Applicable scaling ratio: 1/1000 to 8000 Although any value of 1 to 2 <sup>30</sup> (numerator) and any value of 1 to 2 <sup>30</sup> (denominator) can be used, resulting value should be within the range shown above.					
	Auto tuning		Identifies the load inertia real-time and automatically sets up the gain that meets the stiffness setting when the motor is running with upper and internal operation commands.					
	Notch filter		Available (5 filters available)					
ဂ္ဂ	Gain switching fu	nction	Available					
Comr	Gain switching function		Available					
Commo	2-step torque filter							
Common	2-step torque filte	son output function	Available					
Common	2-step torque filte		Over-voltage, under-voltage, over-speed, over-load, over-heat, over-current,					
Common	2-step torque filte Position comparis	on .						


Panasonic Industry Co., Ltd. | 28 27 | Panasonic Industry Co., Ltd.

# **D-frame (400 V)**




# E-frame (400 V)


A6SF series



# F-frame (400 V)




# **D-frame (400 V)**




# E-frame (400 V)

**A6NF** series



# F-frame (400 V)



Base mount type /Standard:

Back-end mounting

12-M4 ×L6 flat head screw

Unit [mm]

Mass: 2.1 kg

Motor

- XA: ①Main power input terminals @Control power input terminals
- XB: ①Terminals for external regenerative resistor
- X2B : Out for EtherCAT ②Terminals for motor connection

2-5.2

Rack mount type

(Option: Front-end mounting)

X4: I/O connector X5 : Feedback scale connector

X6 : Encoder connector X7: For analog monitor signal connection

170 Mounting bracket Front Panel (Option) X2B XB : Mounting bracket Ground screw For mounting Direction of 40 7.5 air flowing to the internal cooling fan


2-M4 ×L6 flat head screw

D-frame: Connec	tor of driver side	
Connector XA	S03B-JTSLSS-GSANYR (or equivalent)	J.S.T. Mfg. Co., Ltd.
Connector XB	S03B-JTSLSK-GSANXR (or equivalent)	J.S.T. Mfg. Co., Ltd.
Connector XC	S04B-JTSLSK-GSANXR (or equivalent)	J.S.T. Mfg. Co., Ltd.
Connector XD	S02B-J25SK-GGR (or equivalent)	J.S.T. Mfg. Co., Ltd.
Connector X1	UB-M5BR-S14-4S (LF)(SN) (or equivalent)	J.S.T. Mfg. Co., Ltd.
Connector X3	CIF-HS08SK-071-TB (or equivalent)	J.S.T. Mfg. Co., Ltd.
Connector X2A	MOD-WRJ88LY1G-TP+ (or equivalent)	HONDA TSUSHIN KOGYO CO., LTD.
Connector X2B	MOD-WRJ88LY1G-TP+ (or equivalent)	HONDA TSUSHIN KOGYO CO., LTD.
Connector X4	DF02R026NA2 (or equivalent)	Japan Aviation Electronics Ind.
Connector X5	MUF-RS10SK-GKX-TB (LF) (or equivalent)	J.S.T. Mfg. Co., Ltd.
Connector X6	3E106-2230KV (or equivalent)	Sumitomo 3M
Connector X7	53398-8605 (or equivalent)	Japan Molex Inc.
	Connector XA Connector XB Connector XC Connector XD Connector X1 Connector X3 Connector X2A Connector X2B Connector X4 Connector X4 Connector X5 Connector X5 Connector X6	Connector XB S03B-JTSLSK-GSANXR (or equivalent) Connector XC S04B-JTSLSK-GSANXR (or equivalent) Connector XD S02B-J25SK-GGR (or equivalent) Connector X1 UB-M5BR-S14-4S (LF)(SN) (or equivalent) Connector X3 CIF-H508SK-071-TB (or equivalent) Connector X2A MOD-WRJ88LY1G-TP+ (or equivalent) Connector X2B MOD-WRJ88LY1G-TP+ (or equivalent) Connector X4 DF02R026NA2 (or equivalent) Connector X5 MUF-RS10SK-GKX-TB (LF) (or equivalent) Connector X6 3E106-2230KV (or equivalent)

<attached< th=""><th>to the</th><th>drive</th></attached<>	to the	drive
--	--------	-------

Connector of power and motor side			
Connector XA	03JFAT-SAYGSA-L	J.S.T. Mfg. Co., Ltd.	
Connector XB	03JFAT-SAXGSA-L	J.S.T. Mfg. Co., Ltd.	
Connector XC	04JFAT-SAXGSA-L (or equivalent)	J.S.T. Mfg. Co., Ltd.	
Connector XD	02MJFAT-SAGF (or equivalent)	J.S.T. Mfg. Co., Ltd.	

# E-frame (400 V)



**A6BF series** (Please refer to the A6BF series specifications homepage.)

# F-frame (400 V)

